

WHAT IS CLAIMED IS:

Fig. 4 1. A variable gain amplifier, comprising:
an amplifying transistor which amplifies an input
signal; and ¹¹
a current path control section which controls a
size of the ^{12,13} amplifying transistor and a path of a
current through the amplifying transistor.

2. The variable gain amplifier as set forth in
claim 1, wherein:

the current path control section includes a
current control transistor which controls a current
flow through the ¹² amplifying transistor,

said variable gain amplifier comprising:

a plurality of unit circuits ²⁵ which are disposed
parallel to one another, each having the amplifying
transistor and the current control transistor, said
unit circuits being connected to one another through
signal inputs and signal outputs of the unit circuits.

3. The variable gain amplifier as set forth in
claim 2, wherein the amplifying transistor comprises an
amplifying transistor differential pair.

4. The variable gain amplifier as set forth in

208220-18743001

claim 3, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first and second transistor differential pairs to a power source,

wherein gates of transistors which make up the first transistor differential pair and the second transistor differential pair receive oscillation signals which are 180° out of phase from each other.

5. The variable gain amplifier as set forth in claim 3, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair

20250413 14:00

and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs;

a third transistor differential pair and a fourth transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the third transistor differential pair and the fourth transistor differential pair, the third transistor differential pair and the fourth transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first through fourth transistor differential pairs to a power source,

wherein differential inputs of the first and second transistor differential pairs receive first oscillation signals which are 180° out of phase from each other, and differential inputs of the third and fourth transistor differential pairs receive a second oscillation signal which is 90° out of phase from the first oscillation signals.

6. The variable gain amplifier as set forth in

10044-0220

claim 2, wherein respective outputs of the unit circuits are connected to a power source via a load impedance.

7. The variable gain amplifier as set forth in claim 2, further comprising:

a transistor differential pair with a source which is connected to respective outputs of the unit circuits; and

a load impedance which connects outputs of the transistor differential pair to a power source,

wherein gates of transistors which make up the transistor differential pair receive oscillation signals which are 180° out of phase from each other.

8. The variable gain amplifier as set forth in claim 2, comprising:

a variable impedance current mirror circuit, in replacement of the current path control section, which is made up of a plurality of unit current mirror circuits which are disposed parallel to one another and connected to one another through current inputs and current outputs of the unit current mirror circuits, each of the unit current mirror circuits including a first transistor, a second transistor which is paired

2025-03-20 10:30:00

with the first transistor to make up a current mirror, and a switch circuit which switches levels of operation control voltages for the first and second transistors.

9. The variable gain amplifier as set forth in claim 2, further comprising:

a current source which supplies a constant current to the current control transistor of each unit circuit.

10. The variable gain amplifier as set forth in claim 2, wherein each unit circuit includes a switch control circuit which switches levels of operation control voltages for the current control transistor.

11. The variable gain amplifier as set forth in claim 10, wherein the amplifying transistor makes up an amplifying transistor differential pair.

12. The variable gain amplifier as set forth in claim 11, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair

10094494-0339

and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first and second transistor differential pairs to a power source,

wherein gates of transistors which make up the first transistor differential pair and the second transistor differential pair receive oscillation signals which are 180° out of phase from each other.

13. The variable gain amplifier as set forth in claim 11, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs;

a third transistor differential pair and a fourth transistor differential pair, each being provided as

1004194-0300

a load impedance which connects outputs of the first through fourth transistor differential pairs to a power source,

14. The variable gain amplifier as set forth in claim 10, wherein respective outputs of the unit circuits are connected to a power source via a load impedance.

15. The variable gain amplifier as set forth in claim 10, further comprising:

a transistor differential pair with a source which is connected to respective outputs of the unit circuits; and

a load impedance which connects outputs of the transistor differential pair to a power source,

wherein gates of transistors which make up the transistor differential pair receive oscillation signals which are 180° out of phase from each other.

16. The variable gain amplifier as set forth in claim 10, comprising:

a variable impedance current mirror circuit, in replacement of the current path control section, which is made up of a plurality of unit current mirror circuits which are disposed parallel to one another and connected to one another through current inputs and current outputs of the unit current mirror circuits, each of the unit current mirror circuits including a first transistor, a second transistor which is paired with the first transistor to make up a current mirror, and a switch circuit which switches levels of operation control voltages for the first and second transistors.

17. The variable gain amplifier as set forth in claim 10, further comprising:

2025 RELEASE UNDER E.O. 14176

a current source which supplies a constant current to the current control transistor of each unit circuit.

18. The variable gain amplifier as set forth in claim 10, wherein common operation control voltages are inputted to the switch control circuit of each unit circuit.

19. The variable gain amplifier as set forth in claim 18, wherein the amplifying transistor comprises an amplifying transistor differential pair.

20. The variable gain amplifier as set forth in claim 19, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first and second transistor differential pairs to a

2025 RELEASE UNDER E.O. 14176

power source,

wherein gates of transistors which make up the first transistor differential pair and the second transistor differential pair receive oscillation signals which are 180° out of phase from each other.

21. The variable gain amplifier as set forth in claim 19, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs;

a third transistor differential pair and a fourth transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the third transistor differential pair and the fourth transistor differential pair, the third transistor differential pair and the fourth transistor differential pair being connected to a source via

2025 RELEASE UNDER E.O. 14176

different sides of the differential outputs; and

a load impedance which connects outputs of the first through fourth transistor differential pairs to a power source,

wherein differential inputs of the first and second transistor differential pairs receive first oscillation signals which are 180° out of phase from each other, and differential inputs of the third and fourth transistor differential pairs receive a second oscillation signal which is 90° out of phase from the first oscillation signals.

22. The variable gain amplifier as set forth in claim 18, wherein respective outputs of the unit circuits are connected to a power source via a load impedance.

23. The variable gain amplifier as set forth in claim 18, further comprising:

a transistor differential pair with a source which is connected to respective outputs of the unit circuits; and

a load impedance which connects outputs of the transistor differential pair to a power source,

wherein gates of transistors which make up the

20250719 15:00

transistor differential pair receive oscillation signals which are 180° out of phase from each other.

24. The variable gain amplifier as set forth in claim 18, comprising:

a variable impedance current mirror circuit, in replacement of the current path control section, which is made up of a plurality of unit current mirror circuits which are disposed parallel to one another and connected to one another through current inputs and current outputs of the unit current mirror circuits, each of the unit current mirror circuits including a first transistor, a second transistor which is paired with the first transistor to make up a current mirror, and a switch circuit which switches levels of operation control voltages for the first and second transistors.

25. The variable gain amplifier as set forth in claim 18, further comprising:

a current source which supplies a constant current to the current control transistor of each unit circuit.

26. The variable gain amplifier as set forth in claim 18, comprising:

a voltage generator which generates the operation

2025-10-14 14:48:00

control voltages for each unit circuit based on a switch control signal which switches outputs of the switch control circuit.

27. The variable gain amplifier as set forth in claim 26, wherein the amplifying transistor comprises an amplifying transistor differential pair.

28. The variable gain amplifier as set forth in claim 27, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first and second transistor differential pairs to a power source,

wherein gates of transistors which make up the first transistor differential pair and the second transistor differential pair receive oscillation

20250419 14:00:00

signals which are 180° out of phase from each other.

29. The variable gain amplifier as set forth in claim 27, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs;

a third transistor differential pair and a fourth transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the third transistor differential pair and the fourth transistor differential pair, the third transistor differential pair and the fourth transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first through fourth transistor differential pairs to a power source,

20250418T18001

wherein differential inputs of the first and second transistor differential pairs receive first oscillation signals which are 180° out of phase from each other, and differential inputs of the third and fourth transistor differential pairs receive a second oscillation signal which is 90° out of phase from the first oscillation signals.

30. The variable gain amplifier as set forth in claim 26, wherein respective outputs of the unit circuits are connected to a power source via a load impedance.

31. The variable gain amplifier as set forth in claim 26, further comprising:

a transistor differential pair with a source which is connected to respective outputs of the unit circuits; and

a load impedance which connects outputs of the transistor differential pair to a power source,

wherein gates of transistors which make up the transistor differential pair receive oscillation signals which are 180° out of phase from each other.

32. The variable gain amplifier as set forth in

10084194-03300

claim 26, comprising:

a variable impedance current mirror circuit, in replacement of the current path control section, which is made up of a plurality of unit current mirror circuits which are disposed parallel to one another and connected to one another through current inputs and current outputs of the unit current mirror circuits, each of the unit current mirror circuits including a first transistor, a second transistor which is paired with the first transistor to make up a current mirror, and a switch circuit which switches levels of operation control voltages for the first and second transistors.

33. The variable gain amplifier as set forth in claim 26, further comprising:

a current source which supplies a constant current to the current control transistor of each unit circuit.

34. The variable gain amplifier as set forth in claim 26, wherein:

the switch control signal takes a value of either 0 or 1 to activate or deactivate the current control transistor, and

a channel width of the amplifying transistor satisfies

where R is a constant which satisfies

where w_i is a channel width of the amplifying transistor of the unit circuit which corresponds to the switch control signal of an ordinal number i (0, 1, 2, ..., k ; where k is an integer of not less than 0), and W_i is a channel width of i numbers of amplifying transistors whose gain is obtained when i is increased step-wise from 0 by the increment of 1 to increase the number of activated unit circuits according to the operation control voltage which was selected according to the switch control signal to activate the unit circuits.

36. The variable gain amplifier as set forth in claim 35, wherein the amplifying transistor comprises an amplifying transistor differential pair.

37. The variable gain amplifier as set forth in claim 36, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first and second transistor differential pairs to a power source,

wherein gates of transistors which make up the first transistor differential pair and the second transistor differential pair receive oscillation signals which are 180° out of phase from each other.

38. The variable gain amplifier as set forth in claim 36, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each

2025-10-14 14:00:00

other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs;

a third transistor differential pair and a fourth transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the third transistor differential pair and the fourth transistor differential pair, the third transistor differential pair and the fourth transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first through fourth transistor differential pairs to a power source,

wherein differential inputs of the first and second transistor differential pairs receive first oscillation signals which are 180° out of phase from each other, and differential inputs of the third and fourth transistor differential pairs receive a second oscillation signal which is 90° out of phase from the first oscillation signals.

20250415 10:00:00

39. The variable gain amplifier as set forth in claim 35, wherein respective outputs of the unit circuits are connected to a power source via a load impedance.

40. The variable gain amplifier as set forth in claim 35, further comprising:

a transistor differential pair with a source which is connected to respective outputs of the unit circuits; and

a load impedance which connects outputs of the transistor differential pair to a power source,

wherein gates of transistors which make up the transistor differential pair receive oscillation signals which are 180° out of phase from each other.

41. The variable gain amplifier as set forth in claim 35, comprising:

a variable impedance current mirror circuit, in replacement of the current path control section, which is made up of a plurality of unit current mirror circuits which are disposed parallel to one another and connected to one another through current inputs and current outputs of the unit current mirror circuits, each of the unit current mirror circuits including a

2025 RELEASE UNDER E.O. 14176

first transistor, a second transistor which is paired with the first transistor to make up a current mirror, and a switch circuit which switches levels of operation control voltages for the first and second transistors.

42. The variable gain amplifier as set forth in claim 35, further comprising:

a current source which supplies a constant current to the current control transistor of each unit circuit.

43. The variable gain amplifier as set forth in claim 35, wherein the voltage generator varies the level of one of the operation control voltages according to the number of unit circuits with no current supply, so as to control a total amount of a current flow through the remaining unit circuits.

44. The variable gain amplifier as set forth in claim 43, wherein the voltage generator generates the operation control voltages so as to control and maintain the total amount of a current flow at a constant level.

45. The variable gain amplifier as set forth in claim 1, wherein the current path control section

2025-10-14 15:43:00

FIG. 8 46. The variable gain amplifier as set forth in claim 45, wherein:

said variable gain amplifier comprising:

a current source which supplies a constant current
the auxiliary current control transistor.

47. The variable gain amplifier as set forth in

claim 46, wherein the amplifying transistor comprises an amplifying transistor differential pair.

48. The variable gain amplifier as set forth in claim 47, further comprising:

a first transistor differential pair and a second transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the first transistor differential pair and the second transistor differential pair, the first transistor differential pair and the second transistor differential pair being connected to a source via different sides of the differential outputs; and

a load impedance which connects outputs of the first and second transistor differential pairs to a power source,

wherein gates of transistors which make up the first transistor differential pair and the second transistor differential pair receive oscillation signals which are 180° out of phase from each other.

49. The variable gain amplifier as set forth in claim 47, further comprising:

a first transistor differential pair and a second

10044-0330
208220-137800

a third transistor differential pair and a fourth transistor differential pair, each being provided as the amplifying transistor differential pair, with differential outputs which are cross-connected to each other between the third transistor differential pair and the fourth transistor differential pair, the third transistor differential pair and the fourth transistor differential pair being connected to a source via different sides of the differential outputs; and

wherein differential inputs of the first and second transistor differential pairs receive first oscillation signals which are 180° out of phase from each other, and differential inputs of the third and fourth transistor differential pairs receive a second

oscillation signal which is 90° out of phase from the first oscillation signals.

50. The variable gain amplifier as set forth in claim 46, wherein respective outputs of the unit circuits are connected to a power source via a load impedance.

51. The variable gain amplifier as set forth in claim 46, further comprising:

a transistor differential pair with a source which is connected to respective outputs of the unit circuits; and

a load impedance which connects outputs of the transistor differential pair to a power source,

wherein gates of transistors which make up the transistor differential pair receive oscillation signals which are 180° out of phase from each other.

52. The variable gain amplifier as set forth in claim 46, comprising:

a variable impedance current mirror circuit, in replacement of the current path control section, which is made up of a plurality of unit current mirror circuits which are disposed parallel to one another and

203220-18713001

53. The variable gain amplifier as set forth in claim 47, further comprising:

54. The variable gain amplifier as set forth in claim 47, wherein:

a channel width of the amplifying transistor satisfies

where R is a constant which satisfies

where w_i is a channel width of the amplifying transistor of the unit circuit which corresponds to the

switch control signal of an ordinal number i ($0, 1, 2, \dots, k$; where k is an integer of not less than 0), and W_i is a channel width of i numbers of amplifying transistors whose gain is obtained when i is increased step-wise from 0 by the increment of 1 to increase the number of activated unit circuits according to the operation control voltage which was selected according to the switch control signal to activate the unit circuits.